




Main data for Solenoid actuators

Type	Symbol	Voltage	Load	Connection	Weight kg	Order code	
Complete units, solenoid and cable plug							
		24 V ~ 50/60 Hz	8,5 VA	Manual override	22 mm Plug-in	0,17	PRS-A121B
		24 V	6 W	Manual override	22 mm Plug-in	0,17	PRS-A122B
		115 V ~ 50 Hz 120 V ~ 60 Hz	8,5 VA	Manual override	22 mm Plug-in	0,17	PRS-A121F
		230 V ~ 50 Hz 240 V ~ 60 Hz	8,5 VA	Manual override	22 mm Plug-in	0,17	PRS-A121M
Solenoid mounting base							
		For mounting the solenoid coil and plunger on 3-port modular sub-bases type PZU-A●●, see page 18		Manual override	0,09	PRS-D10	
Solenoid coil							
with plunger and 22 mm plug-in connector (4)		24 V*	6 W		0,135	PVA-F102B	
		48 V*	6 W		0,135	PVA-F102E	
		24 VAC 50/60 Hz	8,5 VA		0,135	PVA-F101B	
		48 VAC 50/60 Hz	8,5 VA		0,135	PVA-F101E	
		115 VAC 50 Hz/ 120 VAC 60 Hz	8,5 VA		0,135	PVA-F101F	
		230 VAC 50 Hz	8,5 VA		0,135	PVA-F101M	
		240 VAC 60 Hz					
		255 VAC 50 Hz	8,5 VA		0,135	PVA-F101U	

* Versions available for operation in explosive atmospheres.

- Conforming to certificate LCIE 866115X

- Electrical equipment conforming to harmonised European standards







EN 50014 dated March 1977 (NFC 23514 dated May 1982)

EN 50019 dated March 1977 (NFC 23519 dated May 1982)

- Referencing code EExe II T4 (consult Technical Sales Department)

(4) Can be fitted with LED indicator and suppression, PVA•ZF••

Main data for Pressure switches

Type	Symbol	Electrical characteristics	Pneumatic characteristics		Connection Electric/Pneumatic	Weight kg	Order code
Complete unit with sub-base, solenoid and cable plug							
		N/O contact	override	Manual Plug-in	22 mm Ø4 mm Swivel push-in	0,13	PRE-A12
Without sub-base							
		N/O contact		Manual override	22 mm Plug-in Ø4 mm Swivel push-in	0,04	PRE-A10
Line mounted							
		1 CO contact 5 A/250 V	Fixed operating threshold	Manual override	Ø4 mm Push-in	0,05	PS1-P1081
		1 CO contact 5 A/250 V	Adjustable operating threshold	Manual override	Ø4 mm Push-in	0,05	PS1-P1091

 Indicates stocked product.